



## Features:

- Isolated output & GND for CH1,CH2
- Universal AC input / Full range
- Protections: Short circuit / Overload / Over voltage
- Cooling by free air convection
- LED indicator for power on
- 100% full load burn-in test
- All using 105<sup>°</sup>C long life electrolytic capacitors
- Withstand 300VAC surge input for 5 second
- High operating temperature up to  $70^{\circ}$ C
- · Withstand 5G vibration test
- · High efficiency, long life and high reliability

## **SPECIFICATION**



| MODEL                 |  | RID-85A   |          | RID-85B          |            |
|-----------------------|--|---|----------|------------------|------------|
| ОИТРИТ                | OUTPUT NUMBER  | CH1   | CH2      | CH1              | CH2        |
|                       | DC VOLTAGE   | 5V  | 12V      | 5V               | 24V        |
|                       | RATED CURRENT  | 8A  | 4A       | 8A               | 2A         |
|                       | CURRENT RANGE Note.6   | 2~10A   | 0.3 ~ 5A | 2~10A            | 0.3 ~ 2.5A |
|                       | RATED POWER Note.6   | 88W   |          | 88W              |            |
|                       | RIPPLE & NOISE (max.) Note.2   | 80mVp-p   | 120mVp-p | 80mVp-p          | 120mVp-p   |
|                       | VOLTAGE ADJ. RANGE   | CH1: 4.75 ~ 5.5V  |          | CH1: 4.75 ~ 5.5V |            |
|                       | VOLTAGE TOLERANCE Note.3   | ±2.0%   | ±8.0%    | ±2.0%            | ±5.0%      |
|                       | LINE REGULATION Note.4   | ±0.5%   | ±1.0%    | ±0.5%            | ±1.0%      |
|                       | LOAD REGULATION Note.5   | ±1.0%   | ±3.0%    | ±1.0%            | ±5.0%      |
|                       | SETUP, RISE TIME   | 500ms, 20ms/230VAC 1200ms, 30ms/115VAC at full load   |          |                  |            |
|                       | HOLD UP TIME (Typ.)  | 100ms/230VAC 18ms/115VAC at full load   |          |                  |            |
| INPUT                 | VOLTAGE RANGE  | 88 ~ 264VAC 125 ~ 373VDC (Withstand 300VAC surge for 5sec. Without damage)                        |          |                  |            |
|                       | FREQUENCY RANGE  | 47 ~ 63Hz   |          |                  |            |
|                       | EFFICIENCY(Typ.)   | 80%   |          | 81%              |            |
|                       | AC CURRENT (Typ.)  | 2.5A/115VAC 1.5A/230VAC   |          |                  |            |
|                       | INRUSH CURRENT (Typ.)  | COLD START 40A/230VAC   |          |                  |            |
|                       | LEAKAGE CURRENT  | <2mA/240VAC   |          |                  |            |
| PROTECTION            |  | 110 ~ 150% rated output power   |          |                  |            |
|                       | OVERLOAD   | Protection type: Hiccup mode, recovers automatically after fault condition is removed             |          |                  |            |
|                       | OVER VOLTAGE   | CH1: 5.75 ~ 6.75V   |          |                  |            |
|                       |  | Protection type: Hiccup mode, recovers automatically after fault condition is removed             |          |                  |            |
| ENVIRONMENT           | WORKING TEMP.  | -25 ~ +70°C (Refer to "Derating Curve")   |          |                  |            |
|                       | WORKING HUMIDITY   | 20 ~ 90% RH non-condensing  |          |                  |            |
|                       | STORAGE TEMP., HUMIDITY  | -40 ~ +85°C, 10 ~ 95% RH  |          |                  |            |
|                       | TEMP. COEFFICIENT  | ±0.03%/℃ (0 ~ 50°C) on +5V output   |          |                  |            |
|                       | VIBRATION  | 10 ~ 500Hz, 5G 10min./1cycle, period for 60min. each along X, Y, Z axes                           |          |                  |            |
| SAFETY & EMC (Note 7) | SAFETY STANDARDS   | UL60950-1, TUV EN60950-1 approved   |          |                  |            |
|                       | WITHSTAND VOLTAGE  | I/P-O/P:3KVAC I/P-FG:1.5KVAC O/P-FG:0.5KVAC   |          |                  |            |
|                       | ISOLATION RESISTANCE   | I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C / 70% RH  |          |                  |            |
|                       | EMC EMISSION   | Compliance to EN55022 (CISPR22) Class B, EN61000-3-2,-3   |          |                  |            |
|                       | EMC IMMUNITY   | Compliance to EN61000-4-2,3,4,5,6,8,11, EN61000-6-2 (EN50082-2), heavy industry level, criteria A |          |                  |            |
|                       | MTBF   | 239.4Khrs min. MIL-HDBK-217F (25°C)   |          |                  |            |
|                       | DIMENSION  | 159*97*38mm (L*W*H)   |          |                  |            |
|                       | PACKING  | 0.6Kg; 24pcs/15.4Kg/0.7CUFT   |          |                  |            |
| NOTE                  | <ol> <li>All parameters NOT specially mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature.</li> <li>Ripple &amp; noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf &amp; 47uf parallel capacitor.</li> <li>Tolerance: includes set up tolerance, line regulation and load regulation.</li> <li>Line regulation is measured from low line to high line at rated load.</li> <li>Load regulation is measured from 20% to 100% rated load, and other output at 60% rated load.</li> <li>Each output can work within current range. But total output power can't exceed rated output power.</li> </ol> |   |          |                  |            |

- 7. The power supply is considered a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets EMC directives. For guidance on how to perform these EMC tests, please refer to "EMI testing of component power supplies." (as available on http://www.meanwell.com)
- 8. Length of set up time is measured at cold first start. Turning ON/OFF the power supply very quickly may lead to increase of the set up time.



